

## Flat type proximity sensor

## Features

- Easy to mount in narrow space by flat structure (Height: 10mm)
- Improved the noise resistance with dedicated IC(DC type)
- Built-in reverse polarity protection circuit, overcurrent protection circuit(DC type)
- Built-in surge protection circuit
- Red LED operation indicator
- Protection structure IP67(IEC standard)
- Replaceable for micro switches and limit switches

Please read "Caution for your safety" in operation manual before using.

# Type OC 3-wire type

/!



### ◎ AC 2-wire type

F



※ mark can be customized.

## Specification

Model		PFI25-8DN PFI25-8DN2	PFI25-8DP PFI25-8DP2	PFI25-8AO PFI25-8AC
Sensing distance		8mm		
Hysteresis		Max. 10% of sensing distance		
Standard sensing target		25×25×1mm(Iron)		
Setting distance		0 to 5.6mm		
Power supply (Operating voltage)		12-24VDC (10-30VDC)		100-240VAC (85-264VAC)
Current/Leakage consumption		Max. 10mA		Max. 2.5mA
Response frequency <sup>*1</sup>		200Hz		20Hz
Residual voltage		Max. 1.5V		Max. 10V
Affection by Temp.		Max. ±10% for sensing distance at ambient temperature 20°C		
Control output		Max. 200mA		5 to 150mA
Insulation resistance		Min. 50MΩ(at 500VDC megger)		
Dielectric strength		1,500VAC 50/60Hz for 1 minute		2,500VAC 50/60Hz for 1 minute
Vibration		1mm amplitude at frequency of 10 to 55Hz(for 1 min.) in each of X, Y, Z directions for 2 hours		
Shock		500m/s²(approx. 50G) in each of X, Y, Z directions for 3 times		
Indicator		Operation indicator(red LED)		
Environ- Ambient temperature ment Ambient humidity		-25 to 70°C, storage: -30 to 80°C		
		35 to 95%RH, storage: 35 to 95%RH		
Protection circuit		Surge protection ci Reverse polarity pr Overcurrent protect	rcuit, rotection circuit, tion circuit	Surge protection circuit
Cable		ø4, 3-wire, 2m		ø4, 2-wire, 2m
		(AWG22, Core diameter: 0.08mm, Number of cores: 60, Insulator out diameter: ø1.25)		
Material		Case: PPS, General cable(Black): Polyvinyl chloride(PVC)		
Protection		IP67(IEC standard)		
Approval		CE		
Unit weight		Approx. 70g		

%1: The response frequency is the average value. The standard sensing target is used and the width is set as 2 times of the standard sensing target, 1/2 of the sensing distance for the distance.

※Environment resistance is rated at no freezing or condensation.

## Flat type

## Dimensions



## Control output diagram

## ◎ DC 3-wire type



O AC 2-wire type

## Proper usage

### O Mutual-interference

When several proximity sensors are mounted close to one another a malfunction of the sensor may be caused due to mutual interference. Therefore, be sure to provide a minimum distance between the two sensors as below chart indicates.

## ◎ Influence by surrounding metals

When sensors are mounted on metallic panel, you must prevent the sensors from being affected by any metallic object except target. Therefore, be sure to provide a minimum distance as below chart indicates.



### ООО "РусАвтоматизация"

454010 г. Челябинск, ул. Гагарина 5, оф. 507 тел. 8-800-775-09-57 (звонок бесплатный), +7(351)799-54-26, тел./факс +7(351)211-64-57 info@rusautomation.ru; русавтоматизация.рф; www.rusautomation.ru

(unit: mm)